

# Adore™ iX click and fit Hearing Aid

All data specified were determined under test conditions which comply with the Specifications of Hearing Aid Characteristics ANSI S3.22-2014.

Hearing aid test settings according to the test mode, selectable from the Connexx® fitting menu, configures the instrument for full-on gain, no compression and all adaptive signal analysis and processing turned off.

Battery life stated is measured at 65 dB input and reference test gain.


Actual battery life depends on the output level.

All tests performed with Adore iX.

Standard ANSI S3.22-2014		2 ccm coupler
<b>Output</b>	Peak OSPL 90 HF - average OSPL 90	113 dB 109 dB
<b>Full-on gain</b>	Peak HF-average	50 dB 46 dB
<b>Frequency Range</b>	Low frequency limit High frequency limit	100 Hz 7800 Hz
<b>Total harmonic distortion</b>	500 Hz 800 Hz 1600 Hz 3200 Hz	2% 2% 2% 1%
<b>Equivalent Input Noise</b>		18 dB
<b>Battery Current Drain</b>		1.1 mA
<b>Battery life (typical)</b> 10 zinc air battery		~60 hrs.


## Output Sound Pressure Level

ANSI S3.22-2014



## Frequency Response

ANSI S3.22-2014



Hearing instruments made in Singapore.  
Rev. 10/18 PN 10240640 1.0 RX18807



# Adore™ iX click and fit Hearing Aid

All data specified were determined under test conditions which comply with the Specifications of Hearing Aid Characteristics ANSI S3.22-2014.

Hearing aid test settings according to the test mode, selectable from the Connexx® fitting menu, configures the instrument for full-on gain, no compression and all adaptive signal analysis and processing turned off.

Battery life stated is measured at 65 dB input and reference test gain.


Actual battery life depends on the output level.

All tests performed with Adore iX.

Standard ANSI S3.22-2014		2 ccm coupler
<b>Output</b>	Peak OSPL 90 HF - average OSPL 90	113 dB 109 dB
<b>Full-on gain</b>	Peak HF-average	50 dB 46 dB
<b>Frequency Range</b>	Low frequency limit High frequency limit	100 Hz 7800 Hz
<b>Total harmonic distortion</b>	500 Hz 800 Hz 1600 Hz 3200 Hz	2% 2% 2% 1%
<b>Equivalent Input Noise</b>		18 dB
<b>Battery Current Drain</b>		1.1 mA
<b>Battery life (typical)</b> 10 zinc air battery		~60 hrs.


## Output Sound Pressure Level

ANSI S3.22-2014



## Frequency Response

ANSI S3.22-2014



Hearing instruments made in Singapore.  
Rev. 10/18 PN 10240640 1.0 RX18807



# Adore™ iX click and fit Hearing Aid

All data specified were determined under test conditions which comply with the Specifications of Hearing Aid Characteristics ANSI S3.22-2014.

Hearing aid test settings according to the test mode, selectable from the Connexx® fitting menu, configures the instrument for full-on gain, no compression and all adaptive signal analysis and processing turned off.

Battery life stated is measured at 65 dB input and reference test gain.


Actual battery life depends on the output level.

All tests performed with Adore iX.

Standard ANSI S3.22-2014		2 ccm coupler
<b>Output</b>	Peak OSPL 90 HF - average OSPL 90	113 dB 109 dB
<b>Full-on gain</b>	Peak HF-average	50 dB 46 dB
<b>Frequency Range</b>	Low frequency limit High frequency limit	100 Hz 7800 Hz
<b>Total harmonic distortion</b>	500 Hz 800 Hz 1600 Hz 3200 Hz	2% 2% 2% 1%
<b>Equivalent Input Noise</b>		18 dB
<b>Battery Current Drain</b>		1.1 mA
<b>Battery life (typical)</b> 10 zinc air battery		~60 hrs.


## Output Sound Pressure Level

ANSI S3.22-2014



## Frequency Response

ANSI S3.22-2014



Hearing instruments made in Singapore.  
Rev. 10/18 PN 10240640 1.0 RX18807



# Adore™ iX click and fit Hearing Aid

All data specified were determined under test conditions which comply with the Specifications of Hearing Aid Characteristics ANSI S3.22-2014.

Hearing aid test settings according to the test mode, selectable from the Connexx® fitting menu, configures the instrument for full-on gain, no compression and all adaptive signal analysis and processing turned off.

Battery life stated is measured at 65 dB input and reference test gain.


Actual battery life depends on the output level.

All tests performed with Adore iX.

Standard ANSI S3.22-2014		2 ccm coupler
<b>Output</b>	Peak OSPL 90 HF - average OSPL 90	113 dB 109 dB
<b>Full-on gain</b>	Peak HF-average	50 dB 46 dB
<b>Frequency Range</b>	Low frequency limit High frequency limit	100 Hz 7800 Hz
<b>Total harmonic distortion</b>	500 Hz 800 Hz 1600 Hz 3200 Hz	2% 2% 2% 1%
<b>Equivalent Input Noise</b>		18 dB
<b>Battery Current Drain</b>		1.1 mA
<b>Battery life (typical)</b> 10 zinc air battery		~60 hrs.


## Output Sound Pressure Level

ANSI S3.22-2014



## Frequency Response

ANSI S3.22-2014



Hearing instruments made in Singapore.  
Rev. 10/18 PN 10240640 1.0 RX18807

